

## TSP\_128 AVAILABLE CODES

Code	Inp.	Out.	Analogic Inp.	Analogic Out.
<b>TSP_128/ST</b>	16 PNP	from 0,5A	no	2 from 0..10V 2 PWM
<b>TSP_128/SPT</b>	16 PNP	12 from 0,5A	4 for PT100 (0...300)	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SPT3C</b>	16 PNP	12 from 0,5A	3 for PT100 (0...300) 1 from 0...20mA	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SPT4C</b>	16 PNP	12 from 0,5A	3 for PT100 (-20...+50) 1 from 0...20mA	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SPT5C</b>	16 PNP	12 from 0,5A	2 for PT100 (0...100) 2 from 0...20mA	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SPT6</b>	16 PNP	12 from 0,5A	4 for PT100 (0...100)	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SCT</b>	16 PNP	12 from 0,5A	4 from 0..20 mA	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SCPT</b>	16 PNP	12 from 0,5A	2 for PT100 (0...300) 2 from 0..20 mA	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SCJT</b>	16 PNP	12 from 0,5A	2 from 0..20 mA 2 for TMC J (0..300)	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SC3V1</b>	16 PNP	12 from 0,5A	3 from 0..20 mA 1 from 0...10V	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SCVT</b>	16 PNP	12 from 0,5A	2 from 0...20mA 2 from 0...10V	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SPTP</b>	16 PNP	12 from 0,5A	1 for PT100 (0...300) 1 for pressure sensor 2 from 0...10V (+5V in ADC3)	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SVT</b>	16 PNP	12 from 0,5A	4 from 0..10V	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SCVPT</b>	16 PNP	12 from 0,5A	2 for PT100 (0..300) 1 from 0...10V 1 from 0...20 mA	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SJT</b>	16 PNP	12 from 0,5A	4 for TMC J (0..300)	2 from +/- 10V 2 from 0..10V 2 PWM

<b>TSP_128/SJVT</b>	16 PNP	12 from 0,5A	2 for TMC J (0..300) 2 from 0...10V	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SKT</b>	16 PNP	12 from 0,5A	4 for TMC K (0..400)	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SKU5</b>	16 PNP	12 from 0,5A	2 for TMC K (0..1000) 1 for $\mu$ A Flame Detector 1 from 0...10V	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SKVT</b>	16 PNP	12 from 0,5A	2 for TMC K (0..400) 2 from 0...10V	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/SM6T</b>	16 PNP	12 from 0,5A	1 for PT100 (0..300) 2 from 0..20mA 1 from 0..10V	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/TI</b>	16 PNP	12 from 0,5A	2 from 0...5V 2 from 0..20mA (+5V in J6)	2 from +/- 10V 2 from 0..10V 2 PWM
<b>TSP_128/BIP</b>	16 PNP	12 from 0,5A	1 for PT100 (0..300) 1 for MPX2200 1 from 0..10V	2 from +/- 10V 2 from 0..10V 2 PWM

### Other options:

- **/ETH: Ethernet** option with Web Server function.