

VTP402 AVAILABLE CODES

The VTP_402 can have relays outputs or PNP outputs. For define the correct code first of all you must choose the type of digital outputs you need and the kind of analog inputs you want order. The code must be composed in this way:

VTP_402 / Digital outputs code + analogic inputs code.

Example of complete code: VTP_402 /SPT.

Digital outputs

Code VTP_402/x	Characteristics
S	14 inputs PNP, 8 outputs from 0,5A, 2 outputs from 1A 2 outputs separate groups
R	14 inputs PNP, 8 outputs relays, 2 outputs from 1A The DMX supply 0-24Vdc on static outputs

Analogic inputs outputs

Code VTP_402/Rxxx Or VTP_402/Sxxx	Analogic Inp	Analogic Out	RTC
T	No	2 from 0..10V	YES
A5T	2 for PT100 (0..300) 1 from 0..10V(ADC_1) 1 from 0..5V(ADC_0) +5V instead of +12V on ADC/FROMC	2 from 0..10V	YES
A6T	2 for PT100 (0..300) 1 from 0..20mA(ADC_1) 1 from 0..5V(ADC_0) +5V instead of +12V on ADC/FROMC	2 from 0..10V	YES
PT	2 for PT100 (0..300) 2 from 0..10V	2 from 0..10V	YES
PT1	2 for PT100 (0..100 with 1 decimal resolution) 2 from 0..10V	2 from 0..10V	YES
PT2	2 for PT100 (-20 ..+50) 2 from 0..10V	2 from 0..10V	YES
PT3	1 for PT100 (0..300) 1 for pressure sensor MPX2100 2 from 0..10V +5V instead of +12V on ADC/FROMC	2 from 0..10V	YES
PT4	1 for PT100 (0..100) 3 from 0..20mA	2 from 0..10V	YES
PT5	1 for PT100 (0..300) 3 from 0..10V	2 from 0..10V	YES
JT	2 for TMC J (0..300) 2 from 0..10V	2 from 0..10V	YES
JT1	1 for TMC J (0..300) 1 for pressure sensor MPX2200 2 from 0..10V +5V instead of +12V on ADC/FROMC	2 from 0..10V	YES
JT2	2 for TMC J (0..600) 2 from 0..10V	2 from 0..10V	YES
JT3	2 for pressure sensor 2 from 0..10V	2 from 0..10V	YES
JT4	1 for PT_100 (0...300) 1 for pressure sensor MPX2000 2 from 0...10V	2 from 0...10V	YES
CT	4 from 0..20mA	2 from 0..10V	YES

CodeVTP_402/Rxxx or VTP_402/Sxxx	Analogic Inp.	Analogic Out.	RTC
CPT	2 from 0..20mA 2 for PT100 (0..300)	2 from 0..10V	YES
CPT1	2 for PT100 (-20..+50) 2 from 0..20mA	2 from 0..10V	YES
CV1T	3 from 0...20mA 1 from 0..5	2 from 0..10V	YES
M1T	1 for PT100 (0..300) 1 from 0..20mA 2 from 0..10V	2 from 0..10V	YES
M2T	1 for PT100 (-20..+50) 1 from 0..20mA 2 from 0..10V	2 from 0..10V	YES
M3T	2 from 0..20mA 2 from 0..10V	2 from 0..10V	YES
M4T	2 from 0..5V 2 from 0..10V	2 from 0..10V	YES
M5T	1 for PT100 (-20 +50) 1 from 0..5V 2 from 0..10V	2 from 0..10V	YES
M6T	1 for PT100 (0..300) 2 from 0..20mA 1 from 0..10V	2 from 0..10V	YES
VT	4 from 0..10V	2 from 0..10V	YES
VT5	4 from 0...5V +5V instead of +12V on adc/dac		
VT10	4 from 0..10V +5V instead of +12V on adc/dac	2 from 0..10V	YES
IT	2 for PT100 (0..300) 1 from 0..10V 1 from 0..1V	2 from 0..10V	YES
JVT	1 for TMC J (0..300) 1 from 0..5V 2 from 0..10V	2 from 0..10V	YES
KT	2 for TMC K (0..400) 2 from 0..10V	2 from 0..10V	YES
KVT	1 for TMC K (0..400) 1 from 0..5V 2 from 0..10V	2 from 0..10V	YES
CJT	2 TMC J (0..300) 2 from 0..20mA	2 from 0..10V	YES

Other options:

- /C: Cyrillic display.